



Notes:

- Sensitivity: 265mV at J1.2 = 1 watt.
- Zout = 4 ohms. Intended for 8 ohm speakers.
- Amveco/Tolema toroids available from Digi-Key
- L1 is Hammond.
- C3 is non polarized, not electrolytic
- Response: -7dB at 20Hz, -6dB at 20kHz, -3dB at 40kHz.
- Distortion: About 1% at 2.5W
- Max output = 3.5W per channel.
- Select matched 7695 and matched 6GU5

Title		(c) Copyright, 2003 Steve Bench. All Rights Reserved.	
Size		7695 Matrix Amplifier	
Rev	Document Number	7695 Matrix	
A	7695 Matrix		
Date:		Monday, August 04, 2003	Sheet 1 of 1